# 99150/ HD-25150

# ■ Model No. HD-06120 / HD-25150

Dimension: 650 (L)mm Weight: 2.90 kgs Packing: Box

## ■Crimping Capacity:

Model No.	Rotating dies for cable lugs (mm²)
99150	25, 35, 50, 70, 95, 120, 150

### Features:

- Hexagonal crimping with moveable and rotating dies.
- Multiple rotating dies built in to head, easy to select correct size.
- Longer handles minimize the effort required to produce a perfect crimp.
- Extremely popular tool due to its extended size range.
- Full cycle mechanism releases only after the full crimp cycle is completed.





#### **SAFETY OPERATING & MAINTENANCE INSTRUCTIONS**

### Mechanical Rotatable Crimp Tool

#### HD-25150











#### **WARRANTY**

The KuDos® HD-25120 is warranted to be free of defects in materials and workmanship for a period of 1 year, except in the case of abuse or modification.

#### FEATURES AND BENEFITS

- For cable lugs from 25 to 150 sq.mm hexagonal pressure
- Comfort grip handles and plated jaws
- Multiple crimp selections on a rotatable die wheel
- No tool adjustment required
- Long length results in low handle efforts

#### **OPERATION**

To index die wheel to desired crimp position

- 1) Open handles fully and press die pin (reverse side of the crimp tool, Figure 1).
- 2) Rotate die to the desired crimp groove (Figure 2).
- 3) Release die pin and make sure that the locking plate is back its home position. Cycling the tool without the locking plate back to its home position may result in permanent damage to the die pin.

#### PREVENTIVE MAINTENANCE

The service life of a tool can be greatly improved with proper care and maintenance. To extend the life of your HD-25150 Mechanical Rotatable Crimp Tool, keep it clean and well lubricated every three months.





Read and understand all of the instructions and safety information in this manual before operating or servicing of this tool. Other use of this tool may lead to serious personal injury or death.







Tools are NOT insulated for use on near energized conductors. Use of these tools near energized conductors may lead to electrical shock, causing **DANGER** severe injury or death.